## NLT Rebel/Rebel Plus Cap Lamps

## **SPECIFICATIONS COMPARISON**



nltinc.com

Cap Lamp	Light Output (Typ)	Beam Patterns	Run Time	Weight	Charge Time	Charger Configuration	Water & Dust Protection
Rebel	Bright: 4,800 Lux; Super-Bright: 11,000 Lux	Bright, Super-Bright and Low-Light/ Emergency setting	Bright beam >20 hours; Super-Bright beam >5 hours; Low Light/Emergency setting >7 days	170g (6oz)	<10 Hours	Single, 4, 10, 24 & 48-unit racks; 120V or 240V models	IP67
Rebel Plus	10,000 Lux; Dynamic Turbo Bright: 15,000 Lux Lux	Dual-Beam Technology with 3 beams, Dynamic Turbo Bright and Low-Light/ Emergency setting	Main LED >13 hours; Dynamic Turbo Bright mode only >6 hours; Low-Light/Emergency setting >7 days	170g (6oz)	<10 Hours	Single, 4, 10, 24 & 48-unit racks; 120V or 240V models	IP67





